



The FS/DK drop key fireman switch has a built-in double pole micro-switch. It can be configured as a 'make' switch (*black and blue wires*), a 'break' switch (*violet and green wires*) or both. It can be used with a standard FSK/DK (175E) drop key.

### TERMINAL WIRES

<b>Black:</b>	relay common 1	Push to 'make' switch
<b>Blue:</b>	relay normally open 1	
<b>Violet:</b>	relay common 2	Push to 'break' switch
<b>Green:</b>	relay normally closed 2	

### TECHNICAL SPECIFICATION

<b>Current Rating:</b>	15A at 125Vac 3/4HP, 15A at 250Vac 1 1/2HP
<b>Working Temperature:</b>	-40 to +105°C
<b>Flammability Rating:</b>	UL94HB
<b>Operation Cycles:</b>	6000 ( <i>min operations</i> )

