

WiFi Predator2

Wi-Fi Video Intercom



Search: WIFI PRO 2



OR Scan QR Code









- Simple setup by mobile phone.
- Connect to the intercom directly through your phone's Wi-Fi, enter the pass code for the home hub Wi-Fi and the device is connected.
- View the gate/door and open any time with monitoring mode.
- Full duplex speech.
- 2 Relay Output.
- Latching outputs for hold open.
- CAT5 terminal port for easy hard wire option.
- Upgraded camera, with IR cut filter for better colour by day and IR night vision by night.
- Stores images of the last 32 missed callers on your phone.
- Still works locally on Wi-Fi network even if broadband goes down.
- Can work with most market standard outdoor Wi-Fi repeaters for extended range.



WiFi Predator 2

WiFi Video Intercom



NEW!

GoogleTM
PUSH alerts
on Apple
and Android
devices

Icon based layout















AmazonTM Cloud P2P servers hosted in multiple countries for the fastest connection.



NEW! 2 relays





NEW! Full 2 way Duplex and half Duplex sound options!

NEW! Upgraded camera, with IR cut filter for better colour by day and IR night vision by night



WiFi Predator 2

Wi-Fi / LAN Video Intercom



Technical Details				
Power supply	24v dc (adaptor included)		App name	WIFI PRO 2
Current consumption	80mA standby, 300mA calling		Audio	Full 2 way Duplex and half Duplex sound options
Relay outputs	2		Keypad option	Yes
Relay type	N/O & N/C contacts		Keypad relays	3
Relay time	Adjustable 1-10 secs		Keypad codes	1200
Relay load	2A 24v AC max		Wi-Fi standard	802.11b/g/n
IP rating	IP55		Security	6 digit passcode protected
Camera	Colour, 110 degree, 640x480 pixel			
			Uplink bandwidth	110K bits/sec
Night vision	Yes, by infrared illumination (now with IR cut filter)			